

# MOUNTING BASES



Part Number 45681-210

All Context Plus XP95 smoke and heat detectors fit the Context Plus XP95 mounting base. The base is a zero insertion force base with dual finger receptacles of stainless steel into which the detector terminals slide. Cable connections of up to 2.5mm diameter are made via captive cable clamps.

There are four double terminals and one single terminal.

- L1 line IN and OUT, double terminal
- L2 line IN and OUT, double terminal
- +R remote LED positive supply, double terminal
- R remote LED negative supply, double terminal

The remaining single terminal is isolated and can be used to provide continuity of an earth or shield.

Universal address cards, known as XPERT cards, are supplied with all bases. Consult the coding guide to determine which pips are to be removed. Pre-printed and pre-punched address cards that save time and increase accuracy during commissioning are available in sets (part number: 38531-771).

The base has a 'one way only' fit and detectors can be locked into the base by a grub screw with the aid of a 1.5mm hexagonal driver.

## **NEW** Integrated Base Sounder

The Integrated Base Sounder is a new development from Context Plus and comprises an addressable sounder and base integrated into one unit. It has both individual and group addressing and can be used as a stand-alone unit with a cap or fitted with a Context Plus XP95 detector. The sounder can be set to two tones, a low tone with an output of 55–75dB and a high tone with an output of 75–91dB. An isolated version is also available enabling the isolation of the individual device. Contact our sales desk for availability details.

